

Нууц үг солих болон блок гаргах заавар





"ESIGN client" программ суулгасан байна.

https://esign.gov.mn/esign-client-program

Токен төхөөрөмжийг компьютерт залгана.



SafeNet Authentication Client Tools" программыг ажиллуулна. /ESignClient программ суулгах үед давхар суугдсан байна/



"Advanced view" цэс дээр дарна. /зурагт харуулав/





Set token password" цэсийг дарах /зурагт харуулав/

SafeNet Authenti	cati	on	Clie	nt			Ó	*	9		1	?	æ
	2	1	ş	1	N	0				m	2	1	
	Token	name						MND	0	- 6		-	
B- SafeNet Authentication Client T	Token	catego	ry.					Hardy	vare				
🖻 🤪 Tokens	Reader	name						AKS if	dh 0				
🖻 🕱 MNDC	Serial n	umber	e					0x023	3be1e				
Iser certificates	Total m	nemory	capacit	y .				73728					
🔆 Settings	Free sp	ace	250.0	5				53938					
- 🔯 Client Settings	Hardware version					8.0							



Administrator Password хэсэгт "Үндэсний Дата Төв" УТҮГ-аас өгсөн нууц үгийг оруулан ОК товчийг дарна.

SafeNet SafeNet	Authentication Client
Enter the token's Administrator Passwo	ord.
Token Name:	MNDC
Administrator Password:	Current Language: MN



Шинэ нууц үгийг 2 удаа давтан оруулна.

	SafeNet Authentication Client
Token Password: Confirm Password:	



Доорх линкээр орж файлыг татаж аван задалж ажиллуулна.



Trouver



Программ татах: <u>Татах</u> Программ татах: <u>Татах</u> Программ татах: <u>Татах</u>



Нээгдсэн цонхны баруун доод талын суман дээр дарахад "**Unblock"** товч гарч ирнэ.

🔉 EnterSafe PKI Manager	- ePass3003 - Admin Version		– 🗆 X				
Welcome to EnterSafe F	PKI Manager. Please login.		Login				
ePass3003Auto			Impo <u>r</u> t	🔊 EnterSafe PKI Manager	- ePass3003 - Admin Version		-
			<u>E</u> xport	Welcome to EnterSafe	PKI Manager. Please login.		
		Hide Details-> 💌	Delete	Token list 🗞 ePass3003Auto			Lublock
Field Token Name	Value ePass3003Auto	^	Change User PIN				
Manufacturer Model Serial Number	Feitian Technologies Co., Ltd. ePass3003Auto A572490010250A13		Change <u>T</u> oken Name				Initialize
Total Public Memory Free Public Memory	30000		Cartificata View			Hide Details-> 💌	
Total Private Memory	34000			Field	Value	^	
Free Private Memory	34000			Token Name	ePass3003Auto		
May DIN Longth	16			Manufacturer	Feitian Technologies Co., Ltd.		
			E <u>x</u> it	Model	ePass3003Auto		Change SO PIN
				Serial Number	A572490010250A13		
				Total Public Memory	30000		
				Free Public Memory	30000		
				Total Private Memory	34000		
				Here Private Memory	34000	~	
				May Dist Londra	10		

Exit



"Unblock" товч дээр дарж "SOPIN" дээр "Үндэсний Дата Төв" УТҮГ-аас өгсөн нууц үгийг оруулаад "New user PIN" хэсэгт нууц үгээ зохиож хийгээд, "Confirm" дээр нь давтан хийж "OK" товчийг дарна.

Unblock Ali Asgari.	
SO PIN:	•••••
New user PIN:	
-	🗹 Check intensity 🛛 🚺
Confirm:	•••••
	Enable soft keyboard OK Cancel